

# R2080

## Compact Controller 96 x 96 mm

3-349-216-03  
3/8.14

- **Temperature controller**  
for the direct connection of thermocouples and resistance thermometer Pt100
- **Available as 2-step and 3-step controller with and without time response**
- **Compact housing, front panel dimensions: 96 x 96 mm per DIN 43700**  
For installation to panel switchboards, front panels etc.
- **Easy operation, extensive standard functions and few device variants**
- **Two keys each for function selection and value settings**
- **Replaces GTR 0208**



### Applications

Primary applications include temperature control in plastics processing and packaging machines, oven manufacturing and food processing.

The R2080 controller is suitable for control systems with the following characteristic values:

Characteristic value		
Tu	delay	1 s ... 10 min
Tg	balancing time	1 min ... 10 h
Tg/Tu		> 5

### Features

- Harmonic-free PDPI algorithm
- Proxy setpoint
- Self-optimization
- Heating current monitoring (with external transformer)
- Current settings can be saved as user-defined default settings

### Description

Actual and setpoint values are both displayed digitally at the same time. LEDs indicate the status of switching and alarm outputs, and whether or not manual operation and the proxy setpoint are active.

Control parameters and configuration values are entered with a membrane keypad. Current settings can be saved as user-defined default settings and recalled as required.

Heating current monitoring is provided as a standard feature. Heating current is acquired by means of an external GTZ 4121 current transformer. Acquired values are displayed and evaluated at the R2080 controller.

Error messages are generated if the heating current setpoint is fallen short of, or in the case of antivalence.

### Applicable Regulations and Standards

IEC 61010-1 / DIN EN 61010-1/ VDE 0411 part 1	Safety requirements for electrical equipment for measurement, control and laboratory use
DIN EN 61326 VDE 0843 part 20	Electrical equipment for measurement, control and laboratory use - EMC requirements
DIN VDE 0106 part 1	Protection against electric shock
EN 60529	Degrees of protection provided by enclosures (IP code)

# R2080

## Compact Controller 96 x 96 mm

### Characteristic Values

#### Inputs

Measurement Input	14 bit transformer resolution
Measuring Range	See order information
Sampling Cycle	0.5 s
Offset Compensation	Possible by means of parameter entry

#### Sensor Input Configuration

Sensor Type	Selectable via Keypad	
Thermocouple Pt100	°C/°F configurable	Measuring ranges and designations: see order information

#### Thermocouple

Continuous overload	3 V / 50 Hz AC, sinusoidal 1 V DC
Input impedance	> 50 kΩ
Reference junction	Integrated equalizing circuit
Error messages	For broken sensor, polarity reversal or temperature above or below measuring range

#### Pt100 Resistance Thermometer

	2-Wire Connection	3-Wire Connection
Cable resistance (both directions)	Balancing from 0 to 30 Ω (by means of keystroke with short-circuited sensor)	Compensated from 0 to 30 Ω
Continuous overload	3 V AC / 50 Hz sinusoidal 1 V DC	
Measuring current	approx. 0.2 mA	
Error messages	For broken sensor or short-circuit, or temperature above or below the measuring range	

#### Heating Current Monitoring Input

Measuring range, GTZ 4121 000 R... current transformer input	AC 0 ... 40 A
Measuring range, heating current monitoring input	DC 0 ... 10 V

#### Binary Input

Activation of the proxy setpoint by means of floating contact or isolated electronic switch (optocoupler etc.)

Open circuit voltage approx. 15 V  
Short-circuit current approx. 1.5 mA

Active	Voltage drop via contact	< 2 V
Inactive	Residual current via contact	< 0.02 mA

#### Display

Display range	4-place, digital
Display height	13 mm

#### Status and Switching Outputs

	Symbol	Display Type
Status	W2, Hand	LED
Switching outputs	I, II, A1,A2	LED

#### Controlled Variable

Measuring Range	Display Resolution
All	1 °C or °F; 0.1 °C or °F also with Pt100

#### Heating Current

Measuring Range	Display Resolution
Scalable from 0 to 100.0 A	0.1 A

#### Setpoints

Setpoint limiting	Adjustable upper and lower setting limits
Proxy setpoint	Activation via external contact, value can be programmed at the device

#### Control Performance

##### Configurable Control Modes

PDPI 2-step controller	For heating
PDPI 2-step controller	For cooling
PDPI 3-step controller	
Limit transducer	2 / 3-step controller without time response
Actuator	

Self-optimization By means of keystroke from any mode. Control parameters can be changed manually.

#### Control Parameter Setting Ranges

Display	Meaning	Setting Range
<i>Pb I</i>	Proportional band switching output I	0.1 ... 999,9%
<i>Pb II</i>	Proportional band switching output II (with 3-step controller)	0.1 ... 999,9%
<i>dbnd</i>	Dead spot (for 3-step and step-action controllers)	0 ... MRS <sup>1)</sup>
<i>tu</i>	Path delay	0 ... 9999 s
<i>tc</i>	Read-out cycle time	0.5 ... 600 s

<sup>1)</sup> MRS = measuring range span

#### Outputs

##### Control Outputs

Function	Switching output I (heating) Switching output II (cooling)
Read-out cycle	Adjustable within a range of 0.5 ... 600 s
Output type	Relay or transistor output
Relay output	Floating contact, normally open
Switching capacity	250 V AC / DC, 2 A, 500 VA / 50 W
Service life	> 2 x 10 <sup>5</sup> switching cycles at nominal load
Interference suppression	Provide external RC element (100 Ω - 47 nF) at contactor
CSA	300 V CAT II
Transistor output	Suitable for commercially available semiconductor relays (SSR)

Switching Status	Open-Circuit Voltage	Output Current
Active (load ≤ 800 Ω)	< DC 17 V	10 ... 15 mA
Inactive	< DC 17 V	< 0.1 mA

Overload limit Short-circuit, continuous interruption

# R2080

## Compact Controller 96 x 96 mm

### Heating Current Monitoring

Heating current monitoring	Permanently installed
Current acquisition	Via external current transformer GTZ 4121 000 R.... <sup>*)</sup> (via other external current transformer, scaling required)

<sup>\*)</sup> See data sheet Z 4121 regarding mechanical installation and electrical connection.

Heating current nominal value transfer by means of keystroke

Error Messages for	
– Antivalence	Actuator signal OFF + heating current ON Actuator signal ON + heating current OFF
– Below current setpoint	Below heating current setpoint by more than 20% with actuator signal ON
Signalling	Error message appears on display

### Auxiliary Voltage

Nominal Value	Nominal Range of Use		CSA	Power Consumption
	Voltage	Frequency		
AC 110 V / 230 V	AC 95 V ... 253 V	48 Hz ... 62 Hz	300 V CAT II	Max. 10 VA typ. 6 W

### Accuracy

Controlled Variable Input	Error Limit relative to MRS <sup>1)</sup>	Resolution relative to MRS <sup>1)</sup>
Thermocouple		
– In general, except for types R, S, B	< (0.5% m.v. + 2 K)	< 0.2%
– Types R, S	< 1%	< 0.05%
Resistance thermometers	< 4 K	< 0.1 K
	<b>Error limit</b>	
Reference junction	± 2 K	
	<b>Error limit relative to measured value</b>	<b>Offset error</b>
Heating current input	5%	± 0.1%

<sup>1)</sup> MRS = measuring range span

### Reference Conditions

Reference Quantity	Reference Condition
Ambient temperature Tref	23 °C ± 2 K
Reference junction temperature Tver	23 °C ± 2 K
Auxiliary voltage	Nominal value ± 1% at 50 Hz AC ± 1%, sinusoidal; Allowable common-mode voltage to electrically connected inputs: 0 V DC / AC
Warm-up time	10 min. (inputs within measuring range)

### Ambient Conditions

Annual mean relative humidity, no condensation	75%
Ambient temperature	
– Nominal Range of Use	0 °C ... +50 °C
– Functional range	0 °C ... +50 °C
– Storage range	–25 °C ... +70 °C

### Influencing Quantities and Influence Error

Influencing Quantity	Nominal Range of Use	Maximum Influence Error
Ambient temperature Tu	0 °C ... +50 °C	0.1K (Tu - Tref) / K
Reference junction temperature Tver	0 °C ... +50 °C	0.1 K (Tver - Tref) / K
Cable resistance		
– Thermocouple		
in general, except for types R, S, B	RL = 0 ... 200 Ω	0.4 K / 10 Ω
types R, S	RL = 0 ... 200 Ω	2 K / 10 Ω
– Pt100 2-wire	RL = 0 ... 30 Ω	3 K / Ω (adjustable)
– Pt100 3-wire	RL = 0 ... 30 Ω	0.5K / 10 Ω
Warm-up influence	≤ 5 minutes	± 1%

### Electrical Safety

Safety class	II, panel-mount device per DIN EN 61010-1 section 6.5.4
Contamination Level	1, per DIN EN 61010-1 section 3.7.3.1 and IEC 664
Overvoltage category	II, per DIN EN 61010 appendix J and IEC 664
Operating voltage	300 V per DIN EN 61010

### Electromagnetic Compatibility

Interference emission	EN 61326 measuring method EN 55011, class B limit value		
Interference immunity	EN 61326		
Test type	Standard	Test severity	Criterion
ESD	EN 61000-4-2	4 kV contact discharge	B
		8 kV atmospheric discharge	B
E field	EN 61000-4-3	10 V / m 80 ... 1000 MHz	B
Burst	EN 61000-4-4	2 kV at power supply cables	B
HF	EN 61000-4-6	10 V 0.15 ... 80 MHz, all terminals	A
Surge voltage	EN 61000-4-5	2 kV at all connector cables	A
Voltage dip	EN 61000-4-11	½ period	A

### Mechanical Design

Design	Panel-mount device per DIN 43700 Housing made from plastic per UL V0 Side-by-side mounting with separator ≥10 mm
Front panel dimensions	96 x 96 mm <sup>2</sup>
Installation depth	50 mm
Panel cutout	92 <sup>+0.8</sup> mm x 92 <sup>+0.8</sup> mm
Mounting position	Front panel vertical or tilted back up to 45°
Protection	front panel IP 65 housing IP 20 terminals IP 20
Weight	approx. 0.5 kg

### Standard Equipment

- Controller
- 2 mounting components
- Bilingual operating instructions German/English

# R2080

## Compact Controller 96 x 96 mm

### Order Information

Feature	Designation	
<b>Electronic PDPI controller</b>	R2080	
<b>Controller type</b>		
2-step controller medium time response	A01	
2-step controller with limit contact medium time response	A02	
3-step controller medium time response	A04	
2-step controller short time response	A11	
2-step controller with limit contact short time response	A12	
3-step controller short time response	A14	
without feedback with 1 limit contact	A21	
without feedback with 2 limit contacts	A22	
<b>Measuring ranges</b>		
Thermocouple type L Fe-CuNi 0 ... 200 °C	C01	
	0 ... 400 °C	C02
	0 ... 600 °C	C03
type J Fe-CuNi 0 ... 200 °C	C04	
	0 ... 400 °C	C05
	0 ... 600 °C	C06
	0 ... 800 °C	C07
type K NiCr-Ni 0 ... 400 °C	C08	
	0 ... 600 °C	C09
	0 ... 800 °C	C10
	0 ... 1200 °C	C11
type R Pt13Rh-Pt 0 ... 1600 °C	C12	
type S Pt10Rh-Pt 0 ... 1600 °C	C13	
Resistance thermometer Pt100 0 ... 100 °C	C20	
	0 ... 200 °C	C21
	0 ... 400 °C	C22
	-100 ... +100 °C	C24
	-100 ... +200 °C	C25
<b>Output type 1<sup>st</sup> switching point</b>		
Relay	D1	
Transistor	D2	

the digit zero, you do not need to indicate this type designation in your order.

Features A3, A13, C23 and E3 of controller GTR0208 **cannot be replaced**.

Feature B2 is **not compatible** with GTR0208.

Auxiliary voltage is generally AC 110 ... 230 V.

A switch to deactivate the control outputs is always available (see feature F1 of controller GTR0208).

Generally, the actual value and the setpoint value and/or heating current are indicated.

As a rule, setpoint limiting is available.

### Sample Order

Feature	Designation
<b>Electronic PDPI controller</b>	R2080
2-step controller medium time response	A01
Thermocouple type J Fe-CuNi 400 °C	C05
1 <sup>st</sup> switching point relay	D1

Example of a complete type designation:

**R2080 A01 C05 D1**

When placing your order, please quote the designation of the basic instrument R2080 and, for each additional feature, only one type designation of the same letter. If the letter of a type designation is followed by

### Accessories

Feature	Article number
<b>Current transformer</b> , top-hat rail mounting, for acquiring heating current	
With 3 inputs (one 3-phase consumer or three single-phase AC consumers)	GTZ4121000R0001
With 4 inputs (one 3-phase consumer + one single-phase AC consumer, or four single-phase AC consumers)	GTZ4121000R0002

Edited in Germany • Subject to change without notice • A pdf version is available on the internet

 GOSSEN METRAWATT

GMC-I Messtechnik GmbH  
Südwestpark 15  
90449 Nürnberg • Germany

Phone +49 911 8602-111  
Fax +49 911 8602-777  
E-Mail info@gossenmetrawatt.com  
www.gossenmetrawatt.com